

# ORIGINAL - PLASTIC MF BASE -

Original spare part



## The cost-effective original spare parts

Discover our ORIGINAL signal lamps for printed circuit boards. These lamps with OSRAM's reliable OEM quality feature a wide product range and can be used for instrument and switch lighting.



# Product datasheet

## Technical data

### Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

### General Product Information

Global order reference	2752MF
------------------------	--------

### Electrical Data

Power input	1.8 W
Test voltage	13.5 V
Power input tolerance	±10 %

### Photometric Data

Nominal luminous flux	6.0 lm
Luminous flux tolerance	±20 %

### Colors & materials

Base color	Beige
------------	-------

### Lifetime Data

Lifespan B3	1000 hr
Lifespan Tc	6500 hr

### Capabilities

Thickness of PCB	1.6 mm
Technology	AUX

### Certificates & standards

ECE category	-
Approval marks – approval	-

### Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	16-09-2024
Declaration no. in SCIP database	In work

### Application advice

Product datasheet

For more detailed application information and graphics please see product datasheet.

**Disclaimer**  
Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



**OSRAM**