# **OSRAM**

## ORIGINAL - FESTOON -

## Original spare part





#### The cost-effective original spare parts

The ORIGINAL festoon lamps with OSRAM's reliable OEM quality can be used as original spare parts for a wide range of festoon lamps. The typical application areas of the lamps are number plate and side position lights as well as interior lighting and reading lights.

#### Technical data

#### **Product information**

Application (Category and Product specific)	Auxiliary lamp
---	----------------

#### **General Product Information**

Global order reference	6413


## **Electrical Data**

Power input	5 W
Nominal voltage	12.0 V
Nominal wattage	5 W
Test voltage	13.5 V
Power input tolerance	±10 %

#### **Photometric Data**

Nominal luminous flux	45 lm
Luminous flux tolerance	±20 %

## **Physical Attributes & Dimensions**



Diameter	11.0 mm
Product weight	3.02 g
Length	41.0 mm
Lamp base	SV8.5-8

## **Lifetime Data**

Lifespan B3	1000 hr
Lifespan Tc	2000 hr

#### **Capabilities**

Technology	AUX
------------	-----

#### Certificates & standards

ECE category	-
--------------	---

## **Environmental & Regulatory Information**

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)			
Date of declaration	05-09-2024		
Primary article identifier	4050300891439		
Candidate list substance 1	No declarable substances contained		
Declaration no. in SCIP database	In work		

#### Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4050300891439	OSRA6413	-	-	-

#### Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4050300891439	ORIGINAL FESTOON 6413	Unpacked 1	- x - x -		
4008321093752	ORIGINAL FESTOON 6413	Shipping carton box 50	273 mm x 145 mm x 65 mm	2.57 dm <sup>3</sup>	311.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### **Application advice**

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















# **OSRAM**