Product family datasheet

# **OSRAM**

# ORIGINAL - PLASTIC MF BASE

Original spare part





### The cost-effective original spare parts for trucks

With the ORIGINAL signal lamps for printed circuit boards, OSRAM offers a wide product range of original spare parts for trucks. These lamps provide OSRAM's reliable OEM quality and can be used for instrument and switch lighting.

# Product family datasheet

## Technical data

	Product information		Electrical data				
Product description	Order reference	Application (Category and Product specific)	Power input	Nominal voltage	Nominal wattage	Power input toleranc e	Test voltage
ORIGINAL - PLASTIC MF BASE 2741MFX	2741MFX	Auxiliary lamp	1.6 W	24.0 V	1.20 W	±10 %	28.0 V
ORIGINAL - PLASTIC MF BASE 2741MF	2741MF	Auxiliary lamp	1.6 W	24.0 V	1.20 W	±10 %	28.0 V

	Photometri	Photometrical data		weight	Colors & materials	Lifespan
Product description	Luminous flux	Luminous flux tolerance	Length	Diameter	Base color	Lifespan B3
ORIGINAL - PLASTIC MF BASE 2741MFX	6.4 lm	±25 %	23.5 mm	5 mm	Copper brown	400 h
ORIGINAL - PLASTIC MF BASE 2741MF	6.4 lm	±25 %	23.5 mm	5 mm	Slate grey	400 h

		Additional product data	Environmental information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)		
Product description	Lifespan Tc	Base (standard designation)	Date of Declaration	Primary Article Identifier	Candidate List Substance 1
ORIGINAL - PLASTIC MF BASE 2741MFX	2000 h	BX8.5d	05-03-2024	4008321018984   4008321297211	No declarable substances contained
ORIGINAL - PLASTIC MF BASE 2741MF	2000 h	B8.5d	05-03-2024	4008321018861   4050300891606	No declarable substances contained

Product description	Declaration No. in SCIP database
ORIGINAL - PLASTIC MF BASE 2741MFX	No declarable substances contained
ORIGINAL - PLASTIC MF BASE 2741MF	In work

# Product family datasheet

### **Application advice**

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.





0'0





