

ORIGINAL - PLASTIC MF BASE -

Original spare part



The cost-effective original spare parts for motorcycles

With the ORIGINAL signal lamps for printed circuit boards, OSRAM offers a wide product range of original spare parts for motorcycles. These lamps provide OSRAM's reliable OEM quality and can be used for instrument and switch lighting.

Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference	2352MFX6
------------------------	----------


Electrical Data

Power input	2.13 W
Nominal voltage	12.0 V
Nominal wattage	2 W
Power input tolerance	±10 %
Test voltage	13.5 V

Photometric Data

Nominal luminous flux	11.8 lm
Luminous flux tolerance	±20 %

Physical Attributes & Dimensions



Lamp base	BX8.4d-12.5
Length	17.5 mm
Diameter	5 mm
Product weight	0.74 g

Colors & materials

Base color	Pale green
------------	------------

Lifetime Data

Product datasheet

Lifespan B3	1500 hr
Lifespan Tc	6000 hr

Capabilities

Thickness of PCB	1.25 mm
Technology	AUX

Certificates & standards

ECE category	-
--------------	---

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	19-09-2024
Primary article identifier	4008321097149 4008321011039 4062172046947
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4062172046947	ORIGINAL - PLASTIC MF BASE 2352MFX6	Unpacked 1	- x - x -		
4062172046961	ORIGINAL - PLASTIC MF BASE 2352MFX6	Shipping carton box 50	148 mm x 115 mm x 55 mm	0.94 dm ³	122.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM